

## EMERGENCY CONVERSION KIT LED K-301

Emergency power unit

### Description


Used in LED- or traditional lamp-based in case of a sudden mains power supply failure. Supplied as a kit comprising the following: emergency power supply unit, charge indicator (green LED), Ni-Mg battery, TEST button (for emergency mode operation check, installed inside the box), emergency light LED strip, "A" sticker (used to identify emergency lights). When ordering luminaires by Lighting Technologies with the emergency lighting solution, specify the luminaire part number followed by EM

### Installation

Installed in the luminaire housing.

### Design

Emergency lighting testing and control are performed from a TELEMANDO device.



**Dimensional characteristics**

A	Length	165 mm
B	Width	42 mm
C	Height	36 mm
D	Length (mounting)	162 mm
	Weight	0.4 kg

**Technical features**

1	Article no.	6501000330
2	Power compatibility	3 W
3	Rated voltage	230 V
4	Autonomy in emergency mode	1
5	Battery Ni-Cd	RB 6,0 V 1,2 A*h Ni-Cd
6	Ambient temperature	0 to +40 C
7	Emerg. work type	non maintained
8	Electromagnetic compatibility (EMC)	Yes
9	Climate application	-
10	Housing color	-
11	Electrical shock protection	-